

Product Name	Prod Code	Description	Voltage (V)	Ballast Start Type ²	Ballast Factor Range	32W					28W					Application
						Ballast Factor	Input Watts (W) @ 120V	Input Watts (W) @ 277V	BEF ³ @ 120V	BEF ³ @ 277V	Ballast Factor	Input Watts (W) @ 120V	Input Watts (W) @ 277V	BEF ³ @ 120V	BEF ³ @ 277V	
UltraMax	72258	GE132MAX-L/ULTRA	120/277	I	Low	0.77	25	25	3.08	3.08	0.78	22	22	3.55	3.55	1- F32T8 120 to 277 "L". .77BF UltraMax
UltraMax	49771	GE132MAX-N/ULTRA	120/277	I	Normal	0.87	28	28	3.11	3.11	0.88	25	25	3.52	3.52	1- F32T8 120 to 277"N". .87 BF UltraMax
UltraMax	72259	GE132MAX-N/ULTRA	120/277	I	Normal	0.87	28	28	3.11	3.11	0.88	25	25	3.52	3.52	1- F32T8 120 to 277"N". .87 BF UltraMax
UltraMax	49707	GE232MAX-L/ULTRA	120/277	I	Low	0.77	49	48	1.57	1.60	0.77	44	44	1.75	1.75	2 or 1- F32T8 120 to 277 "L". .77 BF UltraMax
UltraMax	72262	GE232MAX-L/ULTRA	120/277	I	Low	0.77	49	48	1.57	1.60	0.77	43	43	1.79	1.79	2 or 1- F32T8 120 to 277 "L". .77 BF UltraMax
UltraMax	49772	GE232MAX-N/ULTRA	120/277	I	Normal	0.87	54	53	1.61	1.64	0.97	49	48	1.98	2.02	2 or 1- F32T8 120 to 277 "N". .87 BF UltraMax
UltraMax	72266	GE232MAX-N/ULTRA	120/277	I	Normal	0.87	54	53	1.61	1.64	0.97	49	48	1.98	2.02	2 or 1- F32T8 120 to 277 "N". .87 BF UltraMax
UltraMax	71421	GE232MAX-N+	120/277	I	Normal	1.00	63	62	1.59	1.61	1.00	58	57	1.72	1.75	2 or 1- F32T8 120 to 277 "N+" 1.0 BF UltraMax
UltraMax	49775	GE232MAX-H/ULTRA	120/277	I	High	1.15	74	73	1.55	1.58	1.15	66	65	1.74	1.77	2 or 1- F32T8 120 to 277 "H". 1.15 BF UltraMax
UltraMax	49708	GE332MAX-L/ULTRA	120/277	I	Low	0.77	73	72	1.05	1.07	0.77	65	65	1.18	1.18	3 or 2- F32T8 120 to 277 "L". .77 BF UltraMax
UltraMax	71717	GE332MAX-L/ULTRA	120/277	I	Low	0.77	73	72	1.05	1.07	0.77	64	64	1.20	1.20	3 or 2- F32T8 120 to 277 "L". .77 BF UltraMax
UltraMax	49773	GE332MAX-N/ULTRA	120/277	I	Normal	0.87	82	80	1.06	1.09	0.87	72	71	1.21	1.23	3 or 2- F32T8 120 to 277 "N". .87 BF UltraMax
UltraMax	71719	GE332MAX-N/ULTRA	120/277	I	Normal	0.87	82	80	1.06	1.09	0.87	70	70	1.24	1.24	3 or 2- F32T8 120 to 277 "N". .87 BF UltraMax
UltraMax	71422	GE332MAX-N+	120/277	I	Normal	1.00	91	90	1.10	1.11	1.00	83	82	1.20	1.22	3 or 2- F32T8 120 to 277 "N+" 1.0 BF UltraMax
UltraMax	49776	GE332MAX-H/ULTRA	120/277	I	High	1.15	111	109	1.04	1.06	1.15	98	96	1.17	1.20	3 or 2- F32T8 120 to 277 "H". 1.15 BF UltraMax
UltraMax	71714	GE332MAX-H/ULTRA	120/277	I	High	1.18	111	109	1.06	1.08	1.18	95	94	1.24	1.26	3 or 2- F32T8 120 to 277 "H". 1.18 BF UltraMax
UltraMax	49709	GE432MAX-L/ULTRA	120/277	I	Low	0.77	97	96	0.79	0.80	0.77	87	86	0.89	0.90	4 or 3- F32T8 120 to 277 "L". .77 BF UltraMax
UltraMax	71725	GE432MAX-L/ULTRA	120/277	I	Low	0.77	97	96	0.79	0.80	0.77	86	84	0.90	0.92	4 or 3- F32T8 120 to 277 "L". .77 BF UltraMax
UltraMax	49774	GE432MAX-N/ULTRA	120/277	I	Normal	0.87	109	107	0.80	0.81	0.87	98	96	0.89	0.91	4 or 3- F32T8 120 to 277 "N". .87 BF UltraMax
UltraMax	71727	GE432MAX-N/ULTRA	120/277	I	Normal	0.87	109	107	0.80	0.81	0.87	94	92	0.93	0.95	4 or 3- F32T8 120 to 277 "N". .87 BF UltraMax
UltraMax	71423	GE432MAX-N+	120/277	I	Normal	1.00	124	121	0.81	0.83	1.00	114	112	0.88	0.89	4 or 3- F32T8 120 to 277 "N+" 1.0 BF UltraMax
UltraMax	49777	GE432MAX-H/ULTRA	120/277	I	High	1.15	148	145	0.78	0.79	1.15	133	131	0.86	0.88	4 or 3- F32T8 120 to 277 "H". 1.15 BF UltraMax
UltraMax	71723	GE432MAX-H/ULTRA	120/277	I	High	1.18	148	145	0.80	0.81	1.18	127	125	0.93	0.94	4 or 3- F32T8 120 to 277 "H". 1.18 BF UltraMax
UltraMax Bi-Level Sw	71497	GE632MAX-H90-S60	120/277	I	High	1.18	215	218	0.55	0.54						6 5or4 - F32T8 120-277 H 1.18 BF UltraMax 100-60% step dim
UltraMax LoadShed D	71731	GE632MAX-H95-V60	120/277	I	High	1.18	215	218	0.55	0.54						6 5or4 - F32T8 120-277 H 1.18 BF UltraMax 0-10V dimming
UltraStart	96720	GE232-MVPS-L	120/277	P	Low	0.71	47	47	1.51	1.51	0.71	41	41	1.73	1.73	2 or 1 F32T8 120V-277V Low Watt .71 BF UltraStart Program Start
UltraStart	29621	GE-232-120-PS-N	120	P	Normal	0.89	57		1.56		0.85	49		1.73	1.73	2 or 1 F32T8 120V Normal Light .87 BF UltraStart
UltraStart	29622	GE-232-277-PS-N	277	P	Normal	0.89		57		1.56	0.86		49		1.76	2 or 1 F32T8 277V Normal Light .87 BF UltraStart
UltraStart	96714	GE232-MVPS-N	120/277	P	Normal	0.89	59	58	1.51	1.53	0.86	51	50	1.69	1.72	2 or 1 F32T8 120V-277V Normal Light .88 BF UltraStart
UltraStart	29675	GE-232-MVPS-H	120/277	P	High	1.15	75	74	1.53	1.55	1.10	63	62	1.75	1.77	2 F32T8 120V-277V High Light 1.15 BF UltraStart
UltraStart	96721	GE332-MVPS-L	120/277	P	Low	0.71	69	68	1.03	1.04	0.69	58	58	1.19	1.19	3 F32T8 120V-277V Low Watt .71 BF UltraStart
UltraStart	96715	GE332-MVPS-N	120/277	P	Normal	0.89	86	84	1.03	1.06	0.84	73	72	1.15	1.17	3 F32T8 120V-277V Normal Light .88 BF UltraStart
UltraStart	29623	GE-332-120-PS-N	120	P	Normal	0.89	84		1.06		0.84	72		1.17	1.17	3 F32T8 120V Normal Light .88 BF UltraStart
UltraStart	29624	GE-332-277-PS-N	277	P	Normal	0.89		85		1.05	0.84		72		1.17	3 F32T8 277V Normal Light .88 BF UltraStart
UltraStart	29676	GE-332-MVPS-H	120/277	P	High	1.15	110	108	1.05	1.06	1.10	92	91	1.20	1.21	3 F32T8 120V-277V High Light 1.15 BF UltraStart
UltraStart	71832	GE432-MVPS-L	120/277	P	Low	0.71	90	88	0.79	0.81	0.68	77	76	0.88	0.89	4 F32T8 120V-277V Low Watt .71 BF UltraStart
UltraStart	29625	GE-432-120-PS-N	120	P	Normal	0.89	112		0.79		0.84	96		0.88	0.88	4 F32T8 120V Normal Light .87 BF UltraStart
UltraStart	96716	GE432-MVPS-N	120/277	P	Normal	0.89	114	112	0.78	0.79	0.83	96	95	0.86	0.87	4 F32T8 120V-277V Normal Light .88 BF UltraStart
UltraStart	29678	GE-432-MVPS-H	120/277	P	High	1.16	147	144	0.79	0.81	1.12	125	123	0.90	0.91	4 F32T8 120V-277V High Light 1.15 BF UltraStart
ProLine	23672	GE-232-277-N	277	I	Normal	0.89		56		1.59	0.84		48		1.75	2 or 1- F32T8 277V
ProLine	24168	GE-432-277-N	277	I	Normal	0.88		110		0.80	0.84		93		0.90	4 or 3- F32T8 120V "N". .87 BF
MultiVolt ProLine	72269	GE-132-MV-N	120/277	I	Normal	0.87	28	28	3.11	3.11	0.88	25	25	3.52	3.52	1- F32T8 120 to 277 "N". .87 BF
MultiVolt ProLine	72275	GE-232-MV-N	120/277	I	Normal	0.88	57	55	1.54	1.60	0.83	47	47	1.77	1.77	2 or 1- F32T8 120 to 277 "N". .87 BF
MultiVolt ProLine	30255	GE-332-MV-L	120/277	I	Low	0.78	74	73	1.05	1.07	0.75	63	63	1.19	1.19	3 or 2- F32T8 120 to 277
MultiVolt ProLine	30192	GE-332-MV-N	120/277	I	Normal	0.87	81	80	1.07	1.09	0.82	67	66	1.22	1.24	3 or 2- F32T8 120 to 277 "N". .87 BF
MultiVolt ProLine	30199	GE-332-MV-H	120/277	I	High	1.15	113	110	1.02	1.05	1.10	94	92	1.17	1.20	3 or 2- F32T8 120 to 277 "H". 1.15 BF
MultiVolt ProLine	30262	GE-432-MV-L	120/277	I	Low	0.80	100	98	0.80	0.82	0.75	86	85	0.87	0.88	4 or 3- F32T8 120 to 277
MultiVolt ProLine	30193	GE-432-MV-N	120/277	I	Normal	0.88	113	110	0.78	0.80	0.82	93	92	0.88	0.89	4 or 3- F32T8 120 to 277 "N". .87 BF
MultiVolt ProLine	30219	GE-432-MV-H	120/277	I	High	1.15	144	140	0.80	0.82	1.10	122	120	0.90	0.92	4 or 3- F32T8 120 to 277 "H". 1.15 BF