# **Indoor Smart Camera**Specifications

# **Box Contents**



- (1) Cync Indoor Smart Camera
- (1) Power Cord
- (1) Power Brick, White
- (1) Mounting Bracket, White
- (3) Mounting Screws
- (1) Mounting Adhesive
- (1) Security Sticker
- (1) Installation Guide

# **Specifications**

_			۰		
D	e	v	ľ	a	E

Memory Storage Local: SD card slot supports MicroSD Card up to 128GB

Cloud: Supports Cloud storage

Privacy Protection Physical Shutter

Mounting Magnetic Base

Audio I/O Built-in Mic and Speaker

Two-Way Audio Yes

# Camera

**Resolution** Main Stream: 1920 x 1080 (1080P)

Sub Stream: 1280 x 720 (720P)

Video Compression H.264

Video Frame Rate 25 FPS (1080P)

Digital Zoom 8X

Night Vision Distance 8-10 m

Lens Type Glass lens

Viewing Angle 125° diagonal

#### **Environmental**

**Working Humidity** RH < 88% (89.6°F / 32°C)

Environment (West Dry Damp)

(Wet, Dry, Damp)

**Storage Temperature**  $-4^{\circ}\text{F} \text{ to } 140^{\circ}\text{F} \text{ (-20°C to } 60^{\circ}\text{C)}$ 

# **Controls**

Motion Sensor Yes
Wireless Yes

Wireless Protocol Wi-Fi (2.4GHz) and BLE

**Compatibility** Cync Products

**Mobile Compatibility** Works with iOS 12 and above; and Android 9 and above

#### **Certifications**

 FCC ID
 FCC Part 15.247

 IC
 RSS-247

 RoHS
 Compliant

# **Dimensions and Weight**

	Length	Width	Height	Weight
Product	1.42 in	3.10 in	4.78 in	1.25 lbs
	(36.0 mm)	(52.3 mm)	(118.6 mm)	(110 g)



#### **Electrical**

Input Voltage 100~240VAC, 50/60Hz

 Output
 5VDC, 1A


 Connector
 Micro USB

 Power Cord Length
 3.0 m (9.84 ft)

# **Reliability and Warranty**

Warranty 2 Years

#### **Device Overview**



$\widehat{A}$	Privacy	Shutter
~	Tilvuoy	onaccor

(B) Micro SDCard Slot

Solid Blue: Device is booting up

Blinking Blue: Device is in Setup Mode

Off: Device is in Privacy Mode

(C) LED Indicator

**Red:** Device has lost connection to the network / is not responding

**Green:** Device is recording, detecting, or a live stream is being viewed

White: Device is powered on, not detecting

D Reset Button

(E)

MicroUSB Connection